

Product	Document type	Release #	SAP/Doc number	Release date
DVR 440/480 Series	Release notes	V2.0.6		2012.10.18

Video Recorder 440/480 Series new firmware versions

1 DVR 440/480 Series firmware v2.0.6 (date 2012-10-18)

File names:

- 440series.bin (2012-10-12)
- 480series.bin (2012-10-12)

This release includes the following bug fixes:

- In this version unsigned hard disk drives are supported.
The below drives are released and recommended for use in the DVR440/480.

500 GB : ST3500410SV
 ST31000525SV
 WD5000AVDS

1 TB : WD10EURS
 WD10EUDS
 WD10EURX



We do not test other drives than indicated above to verify reliability:

- When using non-Bosch drives in DVR440/480 Series recorders, Bosch can no longer be held liable for any loss or damages or system mal-function resulting from the use of non-Bosch drives.
 - Bosch will provide advance exchange and carry in service only on Bosch products. This means that failing DVR440/480 Series recorders should be returned for repair without non-Bosch drives.
 - Should non-Bosch hard disk drives be returned, then Bosch will not be held responsible for loss of these drives or any information recorded on these drives or for any consequential damages.
 - Bosch will not be held liable for loss or consequential damages resulting from disclosure of any information stored on these non-Bosch drives.
-
- Remote export on low bandwidth networks are supported in this version.

Bosch strongly recommends upgrading to the latest firmware to achieve the best possible functionality, compatibility and performance.

Product	Document type	Release #	SAP/Doc number	Release date
DVR 440/480 Series	Release notes	V2.0.1		2012.04.20

2 Update procedure

To update the DVR 440 or 480 Series to the latest firmware, please refer to the Video recorder 400 Series Operation Manual, chapter 6.6.5 or follow instructions below:

- Put firmware v2.0.6 via a PC on the root of a USB memory stick
 - File name: 440series.bin [date 2012-10-12] for **DVR 440 Series**
 - File name: 480series.bin [date 2012-10-12] for **DVR 480 Series**
- Insert the USB stick into the front USB connector of the DVR
- Log on as "ADMINISTRATOR" in the local unit
- Select **Menu** and go to the "System > Configuration" screen
- Select **Update firmware** to upgrade the DVR software. In this case, the current DVR settings and video will not be deleted or replaced during the update process.




Figure: Update firmware menu

- Select **OK** to begin the update process or click **Cancel** to stop and exit. After the update process is completed you have to press **OK** so that the system will automatically restart.

Alternative a firmware upgrade can be performed via the Web Client:

- Open Internet Explorer and type on the address bar the network IP address of the unit
- Log on by entering the User ID (default ADMINISTRATOR) and Password (default 000000)
- Select the configuration mode by clicking on the "Configuration" button
- Select 'System' and then 'Configuration'
- Browse to the v2.0.6. firmware:
 - File name: 440series.bin [date 2012-10-12] for **DVR 440 Series**
 - File name: 480series.bin [date 2012-10-12] for **DVR 480 Series**
- Press the "Update" button

Firmware will be automatically updated and unit will be restarted.

Product	Document type	Release #	SAP/Doc number	Release date
DVR 440/480 Series	Release notes	V2.0.1		2012.04.20

3 DVR 440/480 Series firmware version history

3.1 Version 1.0.0

File name:

- 440series.bin for **DVR 440 Series**
- 480series.bin for **DVR 480 Series**

Initial firmware version

3.2 Version 1.1.0 (date 2011-12-21)

File names:

- 440series.bin (2011-12-21)
- 480series.bin (2011-12-21)

This release includes the following improvement:

- Setting added to Auto delete video older than 3 days. For some countries this is required by law.
- SMTP port number was default on 587 when SSL is enabled.
 - This port number is now user selectable.

This release includes the following bug fixes were below issues are solved:

- In low or unstable network configurations the DVR sometimes block any network user access until the unit was power cycled.
- It was not possible to record a tour in G3 domes via DVR.
- DVR was losing network gateway in some network applications.
- Network connection was not possible immediately after network disconnect.
- DVR ID in web pages showed one number higher than set in DVR.
- DVR rebooted after a number of smart search actions in web interface.

3.3 Version 2.0.0 (date 2012-04-03)

File names:

- 440series.bin (2012-04-03)
- 480series.bin (2012-04-03)

This release includes the following improvement:

- Web browser support for DVR 600 Series on IE9
- Option to avoid ICMP ping with Control Center (requires CC release v3.35)
 - **Important note:**

Security Systemsystems

Product	Document type	Release #	SAP/Doc number	Release date
DVR 440/480 Series	Release notes	V2.0.1		2012.04.20

- In the new firmware you can set the ICMP to On or Off in the local UI menu 'Network-TCP/IP'
- ICMP must set to **On** to get the DVR connected to a CC version 3.34 or older because in this version of Control Center the ICMP is required
- In the new Control Center version 3.35 the ICMP is not required anymore, therefore in this CC version you can set ICMP to **Off** in the local UI menu 'Network-TCP/IP'
- Email notification with a 10 seconds video clip (10 pictures, iFrame only)
- Low bandwidth support by selecting 256/512kbps bandwidth throttle (iFrame only mode when selecting bandwidth of 256 or 512kbps in local UI)
- PAL or NTSC video format detection is improved (user will be clearly notified when video format of DVR don't match with video format of connected cameras).
- Avoid invalid log-on when user ID is used special characters like /: @ (In this firmware these characters are grayed out and cannot be selected)
- Give warning/possible to cancel before delete video after video format (NTSC/PAL) change

This release includes the following bug fixes were below issues are solved:

- It is possible to use AUX on/off function in Control Center version 3.35
- Dome never stop moving if using PTZ control and drag mouse point

3.4 Version 2.0.1 (date 2012-04-20)

File names:

- 440series.bin (2012-10-12)
- 480series.bin (2012-10-12)

This release includes the following bug fixes:

- Export via web access is not possible when logged-on as 'Advanced User' or 'Normal user' that has rights for export. Always an error is stating that the export file contains 0MB. This has been solved.
- Changing the additional "Normal user settings (like allow playback, search) via the web access was not possible. This is also solved in this release.
- The status information (like video loss, motion alarm, log-on,..) is not shown at the bottom of the Control Center 3.35 in combination with v2.0.0. This is corrected in v2.0.1.